

راهنمای بروزرسانی تجهیزات هایک ویژن





مقدمه

جهت بروزرسانی تجهیزات هایکویژن پس از دریافت فایل فریمور مورد نظر از سایت <u>https://www.hikvision.com/en/</u> میتوانید از دو طریق اقدام به بروزرسانی فریمور نمایید.

نحوه انجام بروزرسانی :

- بروزرسانی از طریق منوی وب :
- الله از دریافت فایل فریمور تجهیزات مورد نظر، مطابق عکس زیر فایل های دریافتی را از حالت فشرده خارج نمایید.

声 FirmwareV5.7.23_241008_S3000605524	2/20/2025 9:47 AM	Compressed (zipp	12,176 KB	- 1
FirmwareV4.74.200_230522_S30005009	2/20/2025 9:44 AM	Compressed (zipp	42,780 KB	- 1
Firmware_V5.7.23_241008_S3000605524	2/20/2025 9:50 AM	File folder		- 1
Firmware_V4.74.200_230522_S30005009	2/20/2025 9:50 AM	File folder		

از مسیر زیر وارد قسمت بروزرسانی شوید 🖈

Configuration->System->Maintenance->Upgrade

I ord I ord I order formation I orde	IIKVISION®	Live View Configuration	🛧 Download Plug-in	👤 admin	E+ Logout
Image: space	🖵 Local	Upgrade & Maintenance Security Audit Log			
Solution Relocit Mathematication Relocit Solution Relocit Solution Relocit Under Managementa Relocit and all parameters, except the IP parameters and user information, is the default settings. Network Default Network Default Vector All Default Default Restore all parameters to default settings. Image Default Default Restore all parameters to default settings. Image Default Default Restore all parameters to default settings. Image Default Default Restore all parameters to default settings. Image Default Default Biowne Imagementa Biowne Imagementa Biowne Imagementa Default Imagementa Biowne Imagementa Defa	System 2				
katerace Recci Recci katerace kater	System Settings	Reboot			
Scorely Default We Management Rester Rester<	Maintenance	Reboot Reboot the device.			
Ver Mangerent Restar Restar Restar Restar Defat Restar <td>Security</td> <td>Default</td> <td></td> <td></td> <td></td>	Security	Default			
Netoric Defauit Notice Notice Defauit Notice Defauit Notice Defauit Restore all parameters to defauit settings. Notice Defauit Defauit <td>User Management</td> <td>Restore Reset all the parameters, except the IP parameters and user information, to the default settings.</td> <td></td> <td></td> <td></td>	User Management	Restore Reset all the parameters, except the IP parameters and user information, to the default settings.			
Notes/adds Internation Export Device Parameters Device Parameters </td <td>Network</td> <td>Default Restore all parameters to default settings.</td> <td></td> <td></td> <td></td>	Network	Default Restore all parameters to default settings.			
I mage Deade Prantentes Deadoe Prantentes Deadoe Informa. Devolead the log, system information and hardware information. Import Config. File Device Prantentes Device Prantente	Video/Audio	Information Export			
	🔝 Image	Device Parameters			
	Event	Diagnose informa Download the log, system information and hardware information.			
Device Parameters Browne Import Status Upgrade Firmware v Browne Upgrade Status Note: The upgrading process will be 1 to 10 minutes, please don't disconnect power to the device during the process. The device reboots automatically after upgrading. Device Auto Maintenance	🗄 Storage	Import Config. File			
Status Upgrade Firmware Status Status Note: The upgrading process will be 1 to 10 minutes, please don't disconnect power to the device during the process. The device reboots automatically after upgrading. Device Auto Maintenance Enable Auto Maintenance C0201 Horison Digital Technology Co., Ltd. All Rights Reserved.		Device Parameters Browse Import			
Upgrade Firmware Browse Status Nose: The upgrading process will be 1 to 10 minutes, please don't disconnect power to the device during the process. The device reboots automatically after upgrading. Device Auto Mainmance	_	Status			
	4	Unorade			
Status Status Note: The upgrading process will be 1 to 10 minutes, please don't disconnect power to the device during the process. The device reboots automatically after upgrading. Device Auto Maintenance Enable Auto Maintenance 02021 Holoson Digital Technology Co., Ltd. All Rights Reserved.					
Note: The upgrading process will be 1 to 19 minutes, please don't disconnect power to the device during the process. The device reboots automatically after upgrading. Device Auto Maintenance Enable Auto Maintenance E00221 Hiorison Digital Technology, Co., Ltd. All Rights Reserved.		Status			
Device Auto Maintenance Enable Auto Maintenance 02021 Hiloision Digital Technology Co., Ltd. All Rights Reserved.		Note: The upgrading process will be 1 to 10 minutes, please don't disconnect power to the device during the process. The device reboots automatically after upgradin	,		
Enable Auto Mantesance 62021 Hilvision Digital Technology Co., Ltd. All Rights Reserved.		Device Auto Maintenance			
62021 Hikvision Digital Technology Co., Ltd. All Rights Reserved.		Enable Auto Maintenance			
		02021 Hitvision Digital Technology Co., Ltd. All Rights Reserved.			

با انتخاب گزینه Browse میتوانید از مسیری که فایل بروزرسانی در آن ذخیره شده فایل مورد نظر را آپلود نمایید



🔶 توجه : حتما فایل از حالت فشرده خارج گردد و فایل digicap انتخاب نمایید.

				,	kc x + -	
	low > Firmware_V5.7.23_241008_S300	~ C	Search Firmware	_v5.7.23_2 P	P tà D ta 🖷 🖕 🗞	(
Organize • New folder			=	: · 🛯 🕜	Learn	more ×
> OneDrive	Name	Date modified	Type	Size	🌟 Downtoad Plug-in 🛽 👤 admin	E+ Logout
	digicap	2/20/2025 9:50 AM	DAV Video	File (VL., 12.1		
Deskte						
🛓 Downloads 🔅						
🚆 Documents 📌						
Nictures 🖈						
🕑 Music 🔹 🖈						
🔁 Videos 🛷					nation, to the default settings.	
- Lavar						
File name: dig	gicap	~	2	~		
File name: dig	gicap	~	*:* Open	Cancel		
File name: dig	gicap Diagnose informa	micaa the iog, system	•:• Open	Cancel		
File name: di	gicap Usignose morma Uox Import Config. File	micaa the iog; system	•:• Open	Cancel		
File name: di	gicap Uragnose morma Uox Import Config. File Device Parameters	micaa ine iog, system	•:• Open Information and na	Cancel	Browse Import	
File name: di	gicap	micaa the log, system	Cpen	Cancel	Browse Import	
File name: de	gicap Usignose momita Uon Import Config. File Device Parameters Status Upgrade	micaa the rag, system	Cpen	Cancel	Browse Inport	
File name da	grap	v	Cpen	Cancel	Erowse Import	
File name da	gicap	vinicaa ine rog; system	Cpen	Cancel aroware insormatio	Browse Import	
File name da	gicap utigenee momita uoo Import Config. File Device Parameters Stutus Stutus Stutus Stutus Stutus Nets: The upgrading process	will be 1 to 10 minute	•:• Open untormation and na	Cancel aroware informatio	Erowse Import	
File name du	grap	will be 1 to 10 minute	•.• Open untormation and na es, please don't dis	Cancel another information	Browse Import Trowse Upgrade the device during the process. The device reboots automatically after upgrading.	
File name da	grap Unigonal storma una Import Config. File Device Parameters Status Upgrade Firmware ♥ Status Nets: The upgrading process Device Autos Mainterance □ Erable Auto Mainterance	will be 1 to 10 minute	t. Open I mormason ano na es, please don't dis	acoware informatio	Browse Import Drowse Upgrade the device during the process. The device reboots automatically after upgrading.	

🔹 پس از انتخاب فایل گزینه <mark>Upgrade</mark> را انتخاب نمایید.

	Eve view Conligu		M. Connost indau	-	E- cogour
) Local	Upgrade & Maintenance	Security Audit Log			
] System	Reboot				
System Settings	Reboot	Reboot the device.			
Security	Default				
User Management	Restore	Reset all the parameters, except the IP parameters and user information, to the default settings.			
Network	Default	Restore all parameters to default settings.			
Image	Information Export Device Parameters				
Event	Diagnose Informa	Download the log, system information and hardware information.			
Storage	Import Config. File				
	Device Parameters	Browse Import			
	Status				
	Eirmware V Status	C UsersLavgfDownloads/Firmware_V5.7.23_241008_ Browse Userade			
	Note: The upgrading pro	cess will be 1 to 10 minutes, please don't disconnect power to the device during the process. The device reboots automatically after upgrading	ng.		
	Device Auto Maintena	nce			
	Enable Auto Maintena	too 02021 Hikvision Diaital Technology Co., Ltd. All Rights Reserved.			
		organis construient onlinent construction (1), onal deals construction).			



🖌 🛛 توجه : پس از بروزرسانی دستگاه به حالت ریبوت (خاموش و روشن) میشود.

	Honorde & Maintenance - Council Audit on	
Local	opginde a meinenance Security Auda Log	
	Reboot	
	Reboot Reboot the device.	
Maintenance	D.L.D.	
	Dentaut Descal at the excemptor, except the D excemptors and user information to the default entires	
	Resource Resource and an parameters, except the in- parameters and use monimation, to the default sealings. Default Resource and increased and the parameters in default searches	
VideorAudio	Information Export Upgrading	
	Device Parameters	
	Diagnose Informa Download the log, system inform atom 62%	
	Import Config. File	
	Device Parameters Browse Import	
	Status	
	Upgrade	
	Firmware V C:Users'Lavaf/Downloads/Firmware_V5.7.23_241008 Browse Upgrade	
	Status	
	Note: The upgrading process will be 1 to 10 minutes, please don't disconnect power to the device during the process. The device reboots automatically after upgrading process.	ding.
	Device Auto Maintenance	
	Enable Auto Maintenance	

IKVISION®	Live View Configuration A Download Plug in 1 admin D Log	jout
D Local	Upgrade & Maintenance Security Audit Log	
	Bahout	
	Reboot Reboot the device.	
Security	Default	
	Restore Reset all the parameters, except the IP parameters and user information, to the default settings.	
Network	Default Restore all parameters to default se vi	
Video/Audio	Information Export	
Image	Device Parameters	
	Diagnose Informa Download the log, system informatic 1. CRebooting	
Storage	Import Config. File	
	Device Parameters	
	Slatus	
	Upgrade	
	Firmware C: UsersiLovel/UownloadsFirmware_V5 / 23 241018 Browse Upgrade	
	Note: The upgrading process will be 1 to 10 minutes, please don't disconnect power to the device during the process. The device reboots automatically after upgrading.	
	Device Auto Maintenance	
	Enable Auto Maintenance	
	62021 Hivesian Digital Technology Co., Lki Ali Rights Reserved.	

توجه: پس از روشن شدن مجدد دستگاه حتما دستگاه را به حالت اولیه کارخانه برگردانید. (تمامی تنظیمات
 پس از بازگردانی به حالت کارخانه حذف میشود که میتوانید پس از راه اندازی مجدد آنها را اعمال نمایید.)



راهاندازی مجدد (Reset Factory) تجهیزات هایکویژن از طریق منوی وب میبایست مراحل زیر را دنبال کنید:

Welcome	
English v	
8 admin	
<u>ه</u>	
Forgot password?	
Log In When using the product, please respect the privacy and other rights of individuals.	

ارد صفحه ورود شده و نام کاربری و رمز عبور را وارد نمایید.

بس از ورود به منوى كالا از مسير زير اقدام به راهاندازي مجدد تنظيمات نماييد.

Maintenance and Security-> Backup and Restore-> Default

KVISION®	2		ୟ ଈି 00 admin ∨
Rest	art Upgrade	Backup and Restore Security Audit Log Device Debugging	
Backup	L		
} iration	Device Parameter	Export	
nance Reset			
curity	Restore to Default Settings	Restore	
		All data except network parameters and user accounts will be cleared.	
	Restore to Factory Settings	Default All functions and purmeters will be restored to factory settings.	
	Import Parameter		
	Device Parameter	Import	

پس از بازگردانی تنظیمات و ریبوت دستگاه میتوانید مجدد تجهیز را راه اندازی نموده و تنظیمات مورد نیاز را
 اعمال نمایید.



- ۲. بروزرسانی از طریق منوی GUI:
- جهت بروزرسانی دستگاه خود از طریق منوی GUI میبایست فایل فریمور را از حالت فشرده خارج نمایید و بر روی
 یک فلش (USB Flash Memory) اضافه نمایید. سپس Flash Memory را از طریق پورت USB به دستگاه
 متصل نمایید، سپس وارد منوی دستگاه شده از مسیر زیر اقدام به بروزرسانی نمایید.

NVR	A (¢			©⊧ ⊙	¢	ч ()
Channel Target Detecti			System Info				
			Network Vide Model DS-7 SN 1620221121CCR Version No. V4.74.2	to Recorder 1616NI-K2 RK93274157WCVU 200. Build 230522			
			Hardware Version Simple Restore Restore to	Factory Defaults			
							n Q
					> 0	¢	16 Matter
		🎲 LG				4.5	

Maintenance (system info) - > Upgrade

 پس از ورود به بخش بروزرسانی از قسمت Local Upgrade نام Flash Memory خودرا انتخاب کرده سپس فایل مرتبط را انتخاب نمایید، پس از بروزرسانی دستگاه خاموش و سپس روشن میشود.

Device Upgrade							×
Local Upgrade	Device Name	USB Flash Disk 1-1		File Format			
Online Upgrade	☆ Upgrade O	Refresh					
	File Name	I File Size	I File Type 💲	Edit Date	I Delete	I Play	
	5		Folder	01-01-1970 00:0	0:00 -		
	📑 digicap.dav	41.78MB		22-05-2023 18:3	5:40 🔟		
				No			
							C
			សិរេទ				Millional



توجه: پس از روشن شدن مجدد دستگاه حتما دستگاه را به حالت اولیه کارخانه برگردانید. (تمامی تنظیمات
 پس از بازگردانی به حالت کارخانه حذف میشود که میتوانید پس از راه اندازی مجدد آنها را اعمال نمایید.)

راهاندازی مجدد (Reset Factory) تجهیزات هایکویژن از طریق منوی GUI میبایست مراحل زیر را دنبال کنید:

🖌 جهت این کار وارد قسمت Maintenance (system info) شوید و گزینه Factory Default را انتخاب نمایید.

NVR	 ۲	R	ø		́О ⊙ 🐛 ҥ ()
Channel Target Detect				System Info	
				Network Video Recorder Model D6:7616NI-K2 SNI 1620221121CCRRK93274157WCVU Version No. V4 74.200 Build 230522	MIKVISION
				Hardware Version B-R Restore all to default a Simple Restore I Factory Default Restore to Inactive	device parameters ettings. S Mike VISION Mere
				+	HIKVISION
				< 1/1	> 1 c c t t t t t t t t t t t t t t t t t
		9	9 LG		

در صورت نیاز به راهنمایی بیشتر، می توانید با تیم پشتیبانی از طریق شماره ۱۶۶۵ تماس بگیرید.